PROFESSIONAL STUDIO & DJ HEADPHONE



HP-525-02

Features

- The HP-525 is specially designed for professional monitoring, e.g. sound reinforcement, studio monitoring and various sound testing.
- Audiophile quality "close-ear", dynamic stereo headphones.
- Super thin 38 mm diaphragm driver offers wide dynamic range and frequency response.
- Neodymium magnet having a high flux density ensures high sensitivity.
- Flexible ear pads and adjustable headband allow the best comfortable wear.
- Detachable phone adaptor plug is available for 1/4" and 1/8" application.
- One ear listening is ideal for DJs.



Use Instruction

- 1. Insert headphone plug to the headphones jack of mixer, amplifier, CD player etc. As soon as 1/8" plug is demanded, please release the 1/4" adaptor plug to submit. (Figure 1)
- 2. Put on headphone directly and make ears to be covered absolutely by the ear pads. Before this action, please make sure correct channels were chosen exactly. The letter R and L on the headband indicate the "right" and "left" channels respectively. (Figure 2)
- 3. Adjust the slide bar to the position that suits your best.(Figure 3)




Figure 1



Figure 2




Figure 3

Caution

- Keep watches or personal credit cards using magnetic coding away from the headphones to prevent possible damage by the headphones' magnetic.
- Avoid listening with the headphones at a loud volume that might affect your hearing after extended play.

Specifications

Driver Unit: 38 mm dia, dynamic type. Frequency response: 20 ~ 20,000Hz.

Impedance: 70Ω .

Sensitivity (at 1 kHz): 106 dB/mW

Input connector: 1/8" gold-plated stereo phone plug and 1/4" phone adaptor.

Power handling capacity: 1W

Net weight: 220 grams (5.3oz) excluding cable

