



FEATURES

- Universal DMX-512 controller
- Controls up to 12 intelligent lights of up to 32 channels each
- 30 banks of 8 scenes, 240 scenes max
- 384 DMX channels of control
- 6 sets of chases containing 240 scenes
- Program fade and speed time into each step
- Reversible sliders
- Re-assignable channels
- Sequential linking of chases
- Assignable pressure-sensitive joystick
- Fog & strobe control buttons
- Grab any fixture on the fly
- Beat activation, tap-sync and auto run
- DMX polarity selector
- 4-space (4U) rack mount
- MIDI compatible

SPECIFICATIONS

- Power: 12VDC 500 mA (external power supply: 100-240VAC 50/60Hz)
- Weight: 7.3lbs (3.3kg)
- Size: 19in x 7in x 2.8in
483mm x 178mm x 71mm