



CS-8

Order No.: 0173550

Price upon request

PRODUCTINFOS

The Automatic Microphone Mixers

of the CS series are THE perfect aid for concepts with multiple microphones, e.g. in conference rooms, churches or language laboratories. The main task of the mixer is to open the respective microphone channel when required and to close it again when the speaker has finished the presentation. This intelligent adjustment for the individual microphone channels allows for a silent and precise control which ensures that the audience hears every single word. This greatly improves the overall sound resulting in a clear, transparent reproduction and minimises acoustic feedback and irritating background noise. The CS mixers feature a last-in function in order to maintain a pleasant atmosphere with a soft ambient sound also during the breaks in conversation rather than just cutting off the sound.

Automatic microphone mixer

- 8 channels
- 3 operating modes: auto mode, priority or 8/1-channel mixer
- Balanced XLR inputs, switchable mic/line
- Additional stereo RCA input
- 48 V phantom power
- Mix output, switchable mic/line
- Trigger outputs for external devices, e.g. warning devices, cameras or speakers
- Status LEDs
- Several devices can be combined via link connections (supplied with cable)
- Desktop metal housing
- 482 mm (19") rack installation possible with supplied mounting brackets

TECHNICAL SPECIFICATIONS

CS-8

No. of channels	8
No. of inputs	8
Mic input	0.2 mV/4.7 k Ω
Line input	60 mV/20 k Ω
Aux output	1 V/200 Ω
Frequency range	35-20,000 Hz
THD	< 0.06%
S/N ratio	> 70 dB
Phantom power	+48 V
Power supply	via encl. plug-in power supply
Admiss. ambient temp.	0-40 °C
Width	420 mm
Height	44 mm
Depth	199 mm
Weight	2.3 kg